

Server ports configuration to accept client connections

Since build [5.2.801](#), WCS is running from 'flashphoner' user for security reasons. However, in this case, if WCS is launched manually from command line

```
cd /usr/local/FlashphonerWebCallServer/bin
sudo ./webcallserver start
```

TCP ports from range 0-1000 cannot be listened because they are not available for non-root users. Therefore, if WCS is launched manually, the following parameters should be changed to use TCP ports from range 1001-65535

- flash_policy.port
- hls.http.port
- hls.https.port
- http.port
- https.port
- rtmp.port
- rtsp.port
- ws.port
- wss.port