

Complete list of CLI commands

Command	Example	Description
add user	add user alice 12345	Add a user with the specified name and password
add app	add app MyApp MyAppKey 'http://localhost'	Add a new application
add app-rest-method	add app-rest-method MyAppKey connect	Add a new REST method to the application
add lb-node	add lb-node --http-port 8081 --flash 1935 --ws 8080 --wss 8443 --max-calls 999 --enabled true 192.168.1.5	Add a node to the load balancer
add authorized_key	add authorized_key -f /root/.ssh/public.pem	Add public key for CLI authorization
grep	grep foo	Search strings using the specified template
passwd	passwd passwd alice	Change the password
reload node-settings	reload node-settings	Reload settings from the flashphoner.properties file
remove app	remove app MyApp	Remove the application with the specified key
remove app-rest-method	remove app-rest-method MyApp ErrorStatusEvent	Remove the REST method from the application
remove lb-node	remove lb-node 192.168.1.5	Remove the node from the load balancer
remove authorized_key	remove authorized_key	Remove CLI authorization public key. This command switches public key authorization off.
save lb-nodes	save lb-nodes	Save nodes of the load balancer to a file
save node-settings	save node-settings	Save current server settings to the flashphoner.properties file
show groups	show groups	Show groups
show users	show users	Show users
show apps	show apps	Show the list of applications
show server-status	show server-status	Show the current server status
show app-status	show app-status MyApp	Show the current status of the specified application
show app-rest-methods	show app-rest-methods MyAppKey	Show the specified application REST methods
show streams	show streams	Show the list of active streams
show lb-nodes	show lb-nodes	Show nodes used in load balancing
show lb-status	show lb-status	Show the current status of the load balancer
show cdn-nodes	show cdn-nodes	Show the list and status of CDN nodes visible to the server (only for <code>cdn_enable=true</code>)
show cdn-routes	show cdn-routes	Show the list of CDN routes and streams CDN (only for <code>cdn_enable=true</code>)
show node-settings	show node-settings	Show or export the list of current WCS settings to a file (see Server settings management)
show node-setting	show node-setting http.address	Show a specific setting from the settings file
start lb	start lb	Start the load balancer
stop lb	stop lb	Stop the load balancer
update user	update user --active false alice	Modify the specified user data

update app	update app --c-class 'com.flashphoner.MyCallbackClass' --m-class 'com.flashphoner.MyMainClass' MyApp	Modify application settings m-class - main class handler. c-class - Callback class handler.
update lb-node	update --http-port 8081 --flash 1935 --ws 8080 --wss 8443 --max-calls 999 --enabled true lb-node 192.168.1.5	Modify the load balancer settings
update node-setting	update node-setting --name http.address --value 127.0.0.1	Modify the value of one option in the settings list