

Using ffmpeg

- [Overview](#)
- [Quick manual on testing](#)
- [Sorenson Spark + Speex 16 kHz stream publishing](#)
 - [Known limits](#)
- [The features](#)
 - [Explicit specification of encoding parameters](#)
 - [Passing parameters to the server when RTMP connection is establishing](#)
 - [How to rotate stream published from ffmpeg](#)

Overview

[ffmpeg](#) is a powerful cross-platform tool for processing and publishing video- and audiocontent. In terms of publishing RTMP stream on server, ffmpeg allows:

- to configure stream encoding parameters very flexible;
- to send RTMP connection parameters to the server.

Quick manual on testing

1. For test we use:

- WCS server
- ffmpeg
- [Player](#) web application in chrome browser to stream playback

2. Launch ffmpeg

```
ffmpeg -re -i BigBuckBunny.mp4 -preset ultrafast -acodec aac -vcodec h264 -strict -2 -f flv rtmp://test1.flashphoner.com:1935/live/stream_ffmpeg
```

Where

- BigBuckBunny.mp4 is a file to publish
- test1.flashphoner.com is WCS server
- stream_ffmpeg is a stream name to publish on server

The stream publishing begins.

3. Open Player application in browser <https://test1.flashphoner.com:8888/client2/examples/demo/streaming/player/player.html>, where test1.flashphoner.com is WCS server. Set the stream name and press 'Play'. The stream playback begins.

Player



WCS URL

wss://test1.flashphoner.com:8443

Stream

stream_ffmpeg

Volume



Sorenson Spark + Speex 16 kHz stream publishing

WCS server can capture RTMP stream encoded with Sorenson Spark + Speex 16kHz to FLV container. This stream can be published, for example, using ffmpeg as follows:

```
ffmpeg -re -i BigBuckBunny.flv -preset ultrafast -ar 16000 -ac 1 -acodec speex -vcodec flv -strict -2 -f flv  
rtmp://test1.flashphoner.com:1935/live/test
```

Known limits

1. To handle such stream including stream recording, the stream will be transcoded to H.264 + AAC.
2. Payload types 127 for video and 97 for audio should be set in SDP when publishing such stream, for example

```
v=0  
o=- 1988962254 1988962254 IN IP4 0.0.0.0  
c=IN IP4 0.0.0.0  
t=0 0  
a=sdplang:en  
m=video 0 RTP/AVP 127  
a=rtpmap:127 FLV/90000  
a=sendonly  
m=audio 0 RTP/AVP 97 8 0  
a=rtpmap:97 SPEEX/16000  
a=rtpmap:8 PCMA/8000  
a=rtpmap:0 PCMU/8000  
a=sendonly
```

The features

Explicit specification of encoding parameters

ffmpeg allows to explicitly set the encoding parameters when stream is publishing, for example

```
ffmpeg -re -i BigBuckBunny.mp4 -acodec aac -vcodec libx264 -f flv -ar 44100 rtmp://127.0.0.1:1935/live/stream_ffmpeg
```

A more complicated case with addition of a sound track to a file that has not one (/dev/zero source is used for example):

```
ffmpeg -re -f lavfi -i "movie=filename=test.mov:loop=0, setpts=N/(FRAME_RATE*TB)" -an -s 1280x720 -r 15 -f rawvideo -pix_fmt yuv420p - | ffmpeg -thread_queue_size 512 -an -f rawvideo -pix_fmt yuv420p -r 15 -s 1280x720 -i - -vn -f s16le -acodec pcm_s16le -ac 2 -i /dev/zero -r 15 -c:v libx264 -tune zerolatency -profile:v baseline -g 60 -b:v 960k -s 1280x720 -c:a aac -b:a 64k -f flv rtmp://127.0.0.1/live/test_video
```

Passing parameters to the server when RTMP connection is establishing

In the "-rtmp_conn" option, ffmpeg allows to set RTMP connection paramtters that should be passed to the server when stream is publishing:

```
ffmpeg -re -i BigBuckBunny.mp4 -f flv -rtmp_conn "0:1 NS:appKey:flashStreamingApp NS:name:12121212 NS:stream:12121212 NO:custom:0:1 NS:auth:22222222 NS:stream:33333333 0:0 0:0" rtmp://test1.flashphoner.com:1935/12121212
```

Here, the following parameters are passed

- server application key flashStreamingApp
- server application name 12121212
- server stream name 12121212
- custom object with additional data:

```
{
  "auth" : "22222222",
  "stream" : "33333333"
}
```

How to rotate stream published from ffmpeg

ffmpeg RTMP encoder allows [to send orientation metadata to WCS server](#) using command line switches:

```
ffmpeg -i input.mp4 -metadata:s:v rotate=90 -vcodec copy -acodec copy -strict -2 -f flv rtmp://test1.flashphoner.com:1935/live/stream_ffmpeg
```

Note that ffmpeg sends orientattion value but notangle itself.